



Dante Network Amplifier

► **High-Powered Amplification**

Dual 30W per channel output ensures powerful and clear audio reproduction.

► **Dante Connectivity**

Integrated Dante technology allows seamless audio networking, enabling efficient and flexible connectivity for various audio devices over a standard Ethernet network.

► **Dual Line Inputs**

Equipped with a 2-channel line input, the amplifier accommodates multiple audio sources, facilitating easy integration with a variety of audio devices such as mixers, media players, or other compatible equipment.

► **Dual Line Outputs**

Enables the expansion of the system's capabilities by routing signals to larger amplifiers for increased power and performance.

► **Speaker Output Options**

The amplifier offers 2-channel speaker outputs, allowing for the connection of stereo speaker setups. This provides a versatile solution for distributing audio to multiple zones or achieving a stereo sound experience in different areas.

► **Versatile Mounting Options**

Supports various installation methods, including desktop placement, wall mounting and 2pcs rack mounting.



Desktop version



Wall mount



1PC rack mount



2PCS rack mount



Model

DANTE-250

Dante Audio Channel	2
Network Port	RJ45
Output Power	2X50W at DC24V, 2X30W at PoE
Input Sensitivity	Line Input: 400MV Network Input: 500MV
Impedance	4OHM
THD	0.1%
SNR	<83dB
Line Input and Output	
Line Input Channel	2
Line Output Channel	2
Input/Output Signal Level	800MV
Balanced Input Impedance	20K Ω
Unbalanced Input Impedance	10K Ω
Distortion	0.008%
SNR	<91dB
Frequency Response	20Hz-20KHz
Power Requirement	24V DC or PoE