

**8 Channel Power Amplifier**
**Features**

- ▶ **Flexible Bridge/Stereo Modes:** Supports 4 × 300W at 4ohm & 8ohm bridged, offering high-power performance for various applications.
- ▶ **8-Channel Link Outputs:** Allows seamless signal distribution and easy system expansion.
- ▶ **8-Channel Balanced Line Inputs:** Ensures superior audio quality with balanced line inputs, reducing noise and interference.
- ▶ **Wide Frequency Response:** Delivers high-fidelity sound across a broad frequency range for optimal audio clarity.
- ▶ **Stereo Sound:** Delivers high-fidelity audio with precise stereo imaging.
- ▶ **Compact & Lightweight:** 1U rack size with a lightweight build for effortless installation and transport.


**Model**
**D-8100**

|                          |  |
|--------------------------|--|
| Output Power             | 8*100W at 8ohm stereo, 8*200W at 4ohm stereo,<br>or 4*300W at 4&8ohm bridged |
| Input Sensitivity        | 0.775V   |
| Frequency Response       | 20Hz-20KHz +1/-1 dB  |
| Input Impedance          | 20K $\Omega$ (BALANCE)/10K $\Omega$ (UNBALANCE)                              |
| THD+N                    | <0.1% @ 8 $\Omega$ 1KHz  |
| Channel Isolation (1KHz) | 60dB(8 $\Omega$ /1KHz)   |
| Operating Voltage        | AC 220V, 50Hz/60Hz   |
| Power Fuse               | 10A  |
| SNR(A-weighted)          | 10dB   |
| Protection Circuit       | Overload, Overheat, Short Circuit  |
| Product Dimensions       | 482x237x44mm   |
| Net Weight               | 4.28Kg   |