

4-CHANNEL WIFI AUDIO AMPLIFIER

Description

WF-4120 is a compact 4 x 120W amplifier with WiFi, Bluetooth, USB and AUX inputs. It is designed to turn the traditional passive speakers into multi-functional wireless speakers. It includes a subwoofer phase switch, with four outputs in stereo mode for stereo sound. In bridged mode, CH1 and CH2 are in subwoofer mode, while CH3 and CH4 are in full-range mode, forming a 2.1 audio system.

Features:

- ▶ Allow wireless music streaming via WiFi or Bluetooth
- ▶ With 4 x 120W stereo speaker outputs
- ▶ With USB reader and AUX input for more audio sources
- ▶ Can adjust volume of each channel independently
- ▶ Supports online music, Internet radio, Airplay, DLNA, Amazon Alexa
- ▶ Convenient music management by WiiM APP



Model	WF-4120
Stereo Mode	
Rated Output Power	4*120W (4ohm)
Input Sensitivity	1V(1KHz)
THD+N	<0.1%
SNR	>90dB
Frequency Responses	20Hz-20KHz -2dB
Bridge Mode	
Rated Output Power	250W(4ohm)
Input Sensitivity	300MV(60Hz)
THD+N	<0.1%
SNR	>90dB
Frequency Responses	20Hz-200Hz
Mic	
Input Sensitivity	300MV
THD+N	<0.1%
SNR	>72dB
Frequency Responses	150Hz-20KHz ±2dB
Product Dimensions	430x265x44mm
Net Weight	3.4kg