



### Power Amplifier

#### Description:

MPA 200 is an installation amplifier which incorporates 3 line inputs(input 1 with bluetooth function), with selector and its own volume control two tone controls and LEDs which mark the signal presence and limit mode. Additionally, the amplifier incorporates microphone input, providing a mixing function and adding several features which set the system according to the installation requirements. These functions that can be set are:

- MIC priority
- Mono/stereo input mode
- 3 gain levels in MIC input
- 3 anti-feedback presets in MIC input



#### SPECIFICATIONS

#### MPA 200

|                      |  |
|----------------------|--|
| Output Power         | 2x 100W @ 8 Ω / 200W (70/100V Line)                        |
| Audio Inputs         | 3 LINE (unbalanced), 1 MIC, 1 RJ45 (RS485 commands)        |
| THD +N               | 1 kHz, 15W, 8 Ω / 16 Ω, 0.1%<br>1 kHz, 30W, 70V/100V, 0.2% |
| Frequency Response   | 20 Hz-20kHz, 0dB - 0.5dB                                   |
| Main Supply AC power | 100 - 240 V, 50/60Hz                                       |
| Dimensions           | 215x48x264mm(WxHxD)  |
| Weight               | 2.3 kg   |